
Temperature Sensor

Electric Vehicle Applications





- ◆Temperature detection of electric motor
- ◆Over-temperature protection of on-board charger
- ◆Over-temperature protection of charging cable
- ◆Over-temperature protection of charging pile
- ◆Temperature detection of battery pack


Application


Electric motor, on-board charger (OBC), battery management system (BMS), charging pile, and charging cable.



www.thinking.com.tw

On-Board Charger Application **Application:** For sensing top, screw-on type is for easy installation and can be installed on metallic surface for temperature detection. Epoxy coating type directly contacts detected object and responds faster. Tubing type offers better resistance of water, heat, and voltage.





Moisture Resistance | 40°C 95% RH X 1000 hours


Operation Temperature | -40~+105°C

Insulation Test | DC 500V 100M Ω (Min)

R Value | R25°C=10KΩ±1% **B Value** | B25/50=3950K±1%

Thermal Time Constant | Around 30 seconds (heating board)

Hi-Pot Test | AC 1500V 10mA (Max)



Component | Sensing top (terminal+NTC chip+epoxy)+lead wire

Moisture Resistance | 40°C 95% RH X 1000 hours


Operation Temperature | -40~+125°C

Insulation Test | DC 500V 100MΩ(Min)

R Value | R25°C=10KΩ±1% **B Value** | B25/85=3435K±1%

Thermal Time Constant | Around 15 seconds (heating board)

Hi-Pot Test | AC 1500V 10mA (Max)



Component | Sensing top (NTC chip+epoxy)+lead wire


Moisture Resistance | 40°C 95% RH X 1000 hours

Operation Temperature | -30~+105°C

Insulation Test | DC 100V 50MΩ(Min)

R Value | R25°C=10KΩ±1% **B Value** | B25/85=3435K±1%

Thermal Time Constant | Around 5 seconds (in water)



Component | Sensing top (NTC chip+epoxy)+cable wire

Moisture Resistance | 40°C 95% RH X 1000 hours

Operation Temperature | -40~+105°C

Insulation Test | DC 100V 50MΩ(Min)

R Value | R25°C=10KΩ±1% **B Value** | B25/85=3435K±1%

Thermal Time Constant | Around 10 seconds (in water)

Hi-Pot Test | AC 1000V 10mA (Max)






Component | Sensing top (NTC chip)+terminal+tube+lead wire

Moisture Resistance | 40°C 95% RH X 1000 hours

Operation Temperature | -20~+80°C

R Value | R25 $^{\circ}$ C=10K Ω ±5% **B Value** | B25/85= 3975K±1%

Thermal Time Constant | Around 11 seconds (in air)



Component | Sensing top (NTC chip+tube)+lead wire **Moisture Resistance** | 40°C 95% RH X 1000 hours

Operation Temperature | -40~+150°C

Insulation Test | DC 500V 100MΩ(Min)

B Value | B25/85=3435K±1% **R Value** | R25 $^{\circ}$ C=10K Ω ±1%


Thermal Time Constant | Around 6 seconds (in water)

Hi-Pot Test | AC 3500V 10mA (Max)



Feature: Maximum operation voltage is increased, and the increase ranges from 125°C to 200°C. For sensing top, screw-on type is for easy installation. Sensing top made of stainless steel is water and corrosion resistant, and it offers stable operation and faster response of the sensor. Φ3mm of the sensor is customizable. Furthermore, tubing type offers better resistance of water and heat. Pt sensor is more stable and accurate.






Component | Sensing top (terminal+plastic cap+NTC chip)+lead wire Moisture Resistance | 40°C 95% RH X 1000 hours

Operation Temperature | -40~+125°C


Insulation Test | DC 500V 100MΩ(Min)

R Value | R25 $^{\circ}$ C=10K Ω ±5% **B Value** | B25/85=3975K±1% **Thermal Time Constant** | Around 20 seconds (heating board)

Hi-Pot Test | AC 1500V 10mA (Max)







Component | Sensing top (NTC chip+tube)+lead wire+tube **Moisture Resistance** | 40°C 95% RH X 1000 hours


Operation Temperature | $-40\sim+200$ °C Insulation Test | DC 500V 100M Ω (Min)


R Value | R185°C=0.1345ΚΩ±1% **B Value** | B25/100=3767K±1% **Thermal Time Constant** | Less than 4 seconds (in water)

Hi-Pot Test | AC 2000V 1sec 5mA(Max)


Charging Cable **Application** **Application:** For sensing top, screw-on type is for easy installation. Epoxy coating type directly detects temperature and responses faster. Tubing type is with better water and heat resistances. Pt sensor offers more accurate temperature detection and better product stability.











Component | Sensing top (terminal+NTC chip+epoxy)+lead wire

Moisture Resistance | 40°C 95% RH X 1000 hours

Operation Temperature | -40~+125°C

Insulation Test | DC 500V 100MΩ(Min)

R Value | R25 $^{\circ}$ C=10K Ω ±1% **B Value** | B25/85=3435K±1%

Thermal Time Constant | Around 30 seconds (heating board)

Hi-Pot Test | AC 1500V 10mA (Max)

Component | Sensing top (terminal+NTC chip+epoxy)+lead wire

Moisture Resistance | 40°C 95% RH X 1000 hours

Operation Temperature | -40~+150°C

Insulation Test | DC 500V 100MΩ(Min)

R Value | R25 $^{\circ}$ C=10K Ω ±1%

B Value | B25/50°C=3950K±1%

Thermal Time Constant | Around 30 seconds (heating board)

Hi-Pot Test | AC 1500V 10mA (Max)

Component | Sensing top (NTC chip+epoxy)+cable wire

Moisture Resistance | 40°C 95% RH X 1000 hours

Operation Temperature | -40~+105°C

Insulation Test | DC 500V 100MΩ(Min)

R Value | R25°C=10K Ω ±1% **B Value** | B25/85=3435K±1%

Thermal Time Constant | Around 10 seconds (in water)

Hi-Pot Test | AC 3500V 10mA (Max)


Component | Sensing top (NTC chip)+tube+terminal+tube+lead wire

Moisture Resistance | 40°C 95% RH X 1000 hours

Operation Temperature | -40~+180°C

R Value | R25 $^{\circ}$ C=10K Ω ±1% **B Value** | B25/85=3435K±1%

Thermal Time Constant | Around 10 seconds (in air)



For charging cable

Component | Sensing top (Pt chip+stainless steel cap)+lead wire Moisture Resistance | 40°C 95% RH X 1000 hours Operation Temperature | -40~+150°C Insulation Test | DC 500V 100MΩ(Min) R Value | R0°C=1000Ω (Class 2B) Temperature Coefficient of Resistance | 3750 ppm

Component | Sensing top (Pt chip+stainless steel cap)+lead wire Moisture Resistance | 40°C 95% RH X 1000 hours

Operation Temperature | -40~+150°C

Insulation Test | DC 500V 100MΩ(Min)


R Value | R0°C=1000 $\pm 4\Omega$ (Class B)


Hi-Pot Test | AC 1500V 10mA (Max)


Temperature Coefficient of Resistance | 3850 ppm

Hi-Pot Test | AC 3500V 10mA (Max)

Battery Pack Application Feature: Multiple-sensor structure offers better PCB layout, and structure or electrical characteristics is customizable in accordance wiht requirement of temperature detection.







Component | Sensing top (NTC chip+epoxy)+lead wire+terminal +housing

Moisture Resistance \[40°C 95% RH X 1000 hours

Operation Temperature | -40~+105°C

Insulation Test DC 500V 100MΩ(Min)

R Value | R25 $^{\circ}$ C=10 K Ω ±1% **B Value** | B25/85°C=3435 K±1%

Thermal Time Constant | Around 10 seconds (in water)

Hi-Pot Test | AC 1000V 10mA (Max)

Component | Sensing top (terminal+NTC chip+epoxy)+lead wire +terminal+housing

Moisture Resistance | 40°C 95% RH X 1000 hours

Operation Temperature | -20~+80°C

Insulation Test DC 500V 100MΩ(Min)

R Value | R25 $^{\circ}$ C=2K Ω ±5% **B Value** | B25/50°C=3500K±2% **Thermal Time Constant** | Around 30 seconds (heating board)

Hi-Pot Test | AC 1500V 10mA (Max)

HEADQUARTER 12F, No.93, Dashun 1st Rd., Zuoying Dist., Kaohsiung, Taiwan 81357 / Tel: 886-7-5577660

TAIPEI, TAIWAN 3F, No.25, Lane 70, Wugong 2nd Rd., Xinzhuang Dist., New Taipei City, Taiwan 24888 / Tel: 886-2-22990652

JIANGSU, CHINA No.6, Longmen Rd., Wujin High & New-Tech Industrial Development Zone, Changzhou, Jiangsu, China 213161 / Tel: 86-519-86578999

GUANGDONG, CHINA No.45, East Rd., Sha-Tao Dist., Chang-An Town, Dongguan City, Guangdong, China 523863 / Tel: 86-769-85542016

BELJING, CHINA Room 2707, Building 1, No. 88, Jian Guo Road, Chaoyang Dist., Beijing City, China 100025 / Tel: 86-010-85898940.

QÍNGDAO, CHINA No.696, Hefei Rd., Shibei Dist., Qingdao City, China 266035 / Tel: 86-138-08993369/86-186-6973899

HUBEL, CHINA California Sunshine Community, Guanggu Rd. Donghu New Technical Development Zone, Wuhan City, Hubei, China / Tel: 86 189 95621889